

Application


1. Back-up UPS system for industrial, commercial, household, etc
2. Mobile power and standby power for areas that lack utility.
3. Off-grid solar & wind power system
 - 3.1 Simple Off-grid solar & wind power system
 - 3.2 AC first Off-grid solar & wind power system
 - 3.3 DC first Off-grid solar & wind power system

Features

1. pure sine wave output, full power
2. CPU management and control, modular design
3. LCD display, can visually display various parameters
4. Multifunction design, can set a variety of working mode
5. External battery connection, convenient to expand use time and back-up power time; user can connect as many batteries as needed
6. With super load carrying ability and high load capacity, this series of inverters can not only drive resistance load; but also various kinds of inductive loads, such as motor, air conditioner, electric drills, fluorescent lamp, gas lamp, etc. It can drive almost any kind of load
7. Low frequency circuit design, good system stability, low failure rate and long service life (under proper operation, it may be as long as 5 years)
8. Perfect protection: low voltage protection, over voltage protection, overheat protection, short-circuit protection, overloads protection; alarm alert
9. CE / EMC / LVD/RoHS Approvals.
10. Two years warranty, life-long technical supports

Function


1. Sole inversion function under inversion mode [only connected to battery], can be set to normal operating mode and sleep mode.



1.1 Normal workingmode□FREQUENCY in the LCD display is set as 01.No matter whether there are AC loads connected to the inverter or not, theinverter’s output terminal will always have voltage ready to supply power to the loads. Under this mode, the LCD will be displayedas bellow:



1.2 Sleep mode□FREQUENCY in the LCD display is set as 02. If the powerof the loads that connected to the inverter is lower than 5% of the inverter’s rated power, there will be no output from theinverter. That is to say, only the chip of inverter is working under suchcondition and the power consumption is only 1-6W; If the power of the loadsthat connected to the inverter is higher than 5% of the inverter’s rated power,then the inverter will automatically start the inversion function and supplypower to the loads within 5s. As shown below:




Load's power< 5% of inverter's rated power



Load's power> 5% of inverter's rated power

2. UPSfunction under utility mode(connected to battery and utility .Can be set asutility first, battery standby mode and battery first, utility standby mode).



2.1 Utility first,battery standby UPS mode: FREQUENCY in the LCD display is set as 01. When both utility and battery are connected to the inverter, utility will supply power to the loads prior to the battery. When utility is cut off, the battery will automatically continue to supply power after inversion.


Steps are as follows:

Step 1: When utility power is available, it will output directly after voltage being stabilized and charge batteries at the same time.

Step 2: When utility power is cut off suddenly, the inverter will convert DC power to AC power automatically to ensure uninterrupted power supply within 5ms.

Step 3: When utility power becomes available again, it will automatically transfer to utility supplying power to loads and charge batteries at the same time.


See Workflow as below.



LCD displayed as below:



Utility supply power and charge battery



Without utility and battery supply power

2.2 Battery first, utility standby UPS mode: FREQUENCY in the LCD display is set as 03. When both utility and battery are connected to the inverter, battery will supply power to the loads prior to utility. When battery capacity is not enough, utility will continue to supply power automatically.


Steps are as follows:

Step 1: When battery has enough power, it will supply power to the loads directly


Step 2: When battery does not have enough power, it will automatically transfer to utility supplying power to the loads

Step 3: After the battery is fully charged (e.g. by solar or wind charge controller), it will then automatically transfer to battery supplying power to the loads.

See Workflow as below.



LCD displayed as bellow:



Battery has power



Battery dead, utility supply power

Parameter

Model	500VA	
Parameter		
Rated Output Capacity	350W	
Peak Power	700W	
Battery Voltage(DC)	12V/24V(optional)	
Size W×D×H(mm)	335*165*375	
Packing Size W×D×H(mm)	355*185*395	
Net Weight (kg)	7	
Gross Weight (kg)	8	
General Parameter		
Working Mode	1	Utility First, Battery Standby

□Setting□	2	Sleep Mode□no utility□load's power higher than 5% of rated power, start to work automatically
	3	Battery first, utility standby
AC Input	Voltage	220V±35% or 110V+35%□optional□
	Frequency	50Hz±3% or 60Hz±3% □optional□
AC Output	Voltage	220V±3% or 230V±3 or 240V±3% or 100V±3% or 110V±3% (optional)
	Frequency	50Hz±0.5 or 60Hz±0.5 (optional)
Battery charge	AC Charge Current	0~15A
	Charge Time	Depend on battery capacity and quantity
	Battery Protection	Automatic detection, Charge and discharge protection□Intelligent Management
Display	Display Mode	LCD
	Display Information	Input voltage□output voltage□output frequency□battery capacity□Load condition□Status Information
Output Wave Type		Pure sine wave output□waveform distortion rate≤3
Overload Ability		□120% 1 min□□130% 10s
Power Consumption	Sleep Mode	1~6W
	Normal Mode	1~3A
Conversion Efficiency		80%~90%
Transfer Time		□5ms □AC to DC / DC to AC□
Protection		Overload output□short-circuit□high-voltage input□low-voltage input□overheat
Environment	Temperature	-10℃□50℃
	Humidity	10%□90%
	Altitude	≤4000m

Remark

The“optional” parameter can be set as per customer's requirement

The above is our standard parameter. Subject to change withoutprior notice.

We have our ownprofessional inverter and controller R&D team and we provide technicalsupport and OEM service.

Others

Please refer tothe outline design, technical documents, product brochures, etc.

Made byEngineering Department May 5, 2014 2nd Edition