Introduction

This is a solar charge controller 20A ~30A that have automatic max. power point tracking function with high efficiency that almost 30%~60% higher than traditional charge controller. It also features the functions of system voltage auto recognition, wide rang of PV input ,charge for all kinds of battery,automatic discharge control,RS 232 / LAN communication function and so on. It is very high-end product for solar market with its best partner I- P-TPI2 model Inverter/Charger/UPS.

Application

- 1. Industrial, commercial, household off grid solar energy generation system
- 2. Movable off grid solar energy generation system
- 3. Communication base stations
- 4. New energy education business
- 5. Solar Monitoring System
- 6. Solar Street Lighting System

Reasons to choose

- 1. 30%-60% solar panels saved
- 1) Conversion efficiency 95%-99%, take most from solar panels
- 2) Charge for all kinds of batteries, 3 charge stage to protect battery. Reduce consumption, cost saved.
- 2. Data monitor and set. Parameters from solar panels like charge current/voltage and IP gate address, total generation power, etc can be showed. 4 kinds DC load control, automaticly save ernergy both from human and solar.
- 3. Lan commucation and RS232 port.
- 4. Software to monitor 100pcs equipments at the same time on one screen on a computer.

Features

- 1.MPPT charge mode, conversion efficiency up to 99%
- 2.12V/24V/48V system auto recognize;
- 3. Wide range of PV input with max. is DC150V.
- 4. Memory function, Save setting function: date, time, generating capacity record and so on .
- 5.Charge mode: 3 stages (fast charge, constant charge ,floating charge) .It prolongs service life of the batteries .
- 6.Discharge mode: ON/OFF mode, double time control mode,PV voltage control mode ,PV voltage+time delay mode and so on .
- 7.Selected battery types: sealed lead acid, vented, gel, NiCd battery. Other types of the batteries can also be defined.
- 8.Most information could be provide by LCD and LED like: model no.,PV input voltage,battery type,battery voltage,charging current,charging power,working status and so on. Also customer's information like company name,website and logo can be added into Solar Eagle software.
- 9.RS232 and LAN communication port. IP and Gate address could be user define it satisfy global area. And communication protocol can be provided to manage all information.
- 10. The upper computer software is displayed in 11 languages, it could show work status and be set parameters of the discharge system.

- 11. With intelligent design, the device can be upgraded online lifelong.
- 12.Compliance with the 2002/95/EC environment protecting demand, doesn't include the Cadmium, hydride and fluoride etc material
- 13.Equipment integrity: controller + CD-ROM(microcomputer software) + communication wire + temperature sensing wire + Anderson terminals;
- 14.CE,ROHS certifications approved.
- 15.2 years warranty. The service life is designed to use for 10 years in theory. Extended 3~10 years warranty service also can be provided.
- 16.CE,ROHS certifications approved.

Technical Specification□

rechnical 5	peci⊓cation⊔⊔			
MODEL:I-P-SMART2-20A/25A/30A - SERIES		20A	25A	30A
Charge Mode		Maximum Power Point Tracking		
Discharge Mode		Intelligent control		
System Type		12V 24V 48V Automatic recognition		
Soft Start Time		≤ 10S		
Dynamic Response Recovery Time		500us		
Conversion Efficiency		≥96.5%,≤99%		
PV Modules Utilization Rate		≥99%		
		NPUT CHARACTERIS	STICS	
MPPT Working Voltage and	12V system	DC18V~DC150V		
	24V system	DC34~DC150V		
Range	48V system	DC65~DC150V		
Low Voltage Input Protection Point	12V system	DC16V		
	24V system	DC30V		
	48V system	DC60V		
Low Voltage Input Recovery Point	12V system	DC22V		
	24V system	DC34V		
	48V system	DC65V		
Max. DC Voltage		DC160V		
Input Overvoltage Protection Point		DC150		
Input Overvoltage Recovery Point		DC145V		
Max. PV Power	12V system	286W	357W	429W
	24V system	572W	715W	858W
	48V system	1144W	1430W	1716W
	Cl	HARGE CHARACTER		
Selectable Battery Types		Sealed lead acid, vented, Gel, NiCd battery(Default type is GEL battery)		
Other types of Battery Setting		Constant charge		tant/floating charge ween DC10V~DC15 (
		Floating charge	based on 1 pcs 12V battery)	
Battery Type Setting		12V/24V/48V SYS	Controller and	d upper monitor

O. T.	12) //2 4) //40) / 6) /6	Three Stages :Fa	ast charge/Constant			
Charge Type	12V/24V/48V SYS		pating charge			
Rated Output Current	20A	25A	30A			
Current-limiting Protection	25A	30A	35A			
Temperature Factor	±0.02%/°C					
Temperature Compensation	14.2V-(The highest temperature-25°C)*0.3					
Output Ripples(peak)	200mV					
Output Voltage Stability Precision	≤±1.5%					
Charge voltage Peak-Peak Ripple	200mV					
Charger voltage accuracy	≤±1.5%					
DISCHARGE CHARACTERISTICS						
Setting Control		Controller or LAN	N .			
Max discharge current	42014	30A	1.0004/			
Max discharge power	420W	840W fuse 40A*2	1680W			
Discharge protection			in minut off in minut			
Double-time control	On in morning ,off in morning / On in night ,off in night ON / OFF					
ON / OFF mode PV voltage control	PV voltage on,PV voltage off					
PV voltage control	PV voltage on, time delay off					
1 V Voltage / time delay control						
Discharge voltage protection	Output off when it under setting voltage; Factory set is 10.5 .(Note : set based on 1 battery)					
			1 battery /			
RS232 Communication	Character Charac	ORT se COM communi	cation			
RS232 Communication						
LAN Communication	Set IP and Gate address for controller and solar eagle ;Then chose TCP communication					
PROTECTIONS						
	PROTECTIONS					
Input Low Voltage Protection	PROTECTIONS					
Input Low Voltage Protection Input Overvoltage Protection	PROTECTIONS					
		he in/output chara	acteristics			
Input Overvoltage Protection		he in/output chara	acteristics			
Input Overvoltage Protection Input Polarity Reversal Protection	Check t	he in/output chara	acteristics			
Input Overvoltage Protection Input Polarity Reversal Protection Output Overvoltage Protection Output Polarity Reversal Protection	Check t					
Input Overvoltage Protection Input Polarity Reversal Protection Output Overvoltage Protection	Check t Recover after e		ort-circuit fault, no			
Input Overvoltage Protection Input Polarity Reversal Protection Output Overvoltage Protection Output Polarity Reversal Protection	Check t Recover after e problen	liminating the Sho n for long term Sh 95°C	ort-circuit fault, no ort-circuit			
Input Overvoltage Protection Input Polarity Reversal Protection Output Overvoltage Protection Output Polarity Reversal Protection Short-circuit Protection Temperature Protection	Check t Recover after e problen	liminating the Sho n for long term Sh 95°C ase the output pov	ort-circuit fault, no			
Input Overvoltage Protection Input Polarity Reversal Protection Output Overvoltage Protection Output Polarity Reversal Protection Short-circuit Protection	Recover after e problen Above 85°C,decrea	liminating the Sho n for long term Sh 95°C ase the output poo degree.	ort-circuit fault, no ort-circuit			
Input Overvoltage Protection Input Polarity Reversal Protection Output Overvoltage Protection Output Polarity Reversal Protection Short-circuit Protection Temperature Protection Temperature protection	Check t Recover after e problen	liminating the Sho n for long term Sh 95°C ase the output pow degree.	ort-circuit fault, no ort-circuit			
Input Overvoltage Protection Input Polarity Reversal Protection Output Overvoltage Protection Output Polarity Reversal Protection Short-circuit Protection Temperature Protection	Recover after e problen Above 85°C,decrea	liminating the Shoon for long term Shoon 95°C ase the output powdegree. RS ≤40dB	ort-circuit fault, no ort-circuit wer, decrease 3A per			
Input Overvoltage Protection Input Polarity Reversal Protection Output Overvoltage Protection Output Polarity Reversal Protection Short-circuit Protection Temperature Protection Temperature protection Noise	Recover after e problen Above 85°C,decrea OTHER PARAMETE Forced air coo	liminating the Shoon for long term Shoon 95°C ase the output pool degree. RS ≤40dB oling, fan speed ra	ort-circuit fault, no ort-circuit wer, decrease 3A per			
Input Overvoltage Protection Input Polarity Reversal Protection Output Overvoltage Protection Output Polarity Reversal Protection Short-circuit Protection Temperature Protection Temperature protection	Recover after e problen Above 85°C,decrea OTHER PARAMETE Forced air codtemperature, when	liminating the Shoon for long term Shoon 95°C ase the output powdegree. RS ≤40dB Soling, fan speed ran inner temperatu	ort-circuit fault, no ort-circuit wer, decrease 3A per			
Input Overvoltage Protection Input Polarity Reversal Protection Output Overvoltage Protection Output Polarity Reversal Protection Short-circuit Protection Temperature Protection Temperature protection Noise	Recover after e problen Above 85°C,decrea OTHER PARAMETE Forced air codtemperature, when	liminating the Shoon for long term Shoon 95°C ase the output powdegree. RS ≤40dB Soling, fan speed ran inner temperatu	ort-circuit fault, no ort-circuit wer, decrease 3A per ate regulated by re is too low, fan ran			
Input Overvoltage Protection Input Polarity Reversal Protection Output Overvoltage Protection Output Polarity Reversal Protection Short-circuit Protection Temperature Protection Temperature protection Noise	Recover after e problen Above 85°C,decrea OTHER PARAMETE Forced air cod temperature, when slowly or stop; when world brand recommendations are shown as a stop of the content of the co	liminating the Shoon for long term Shoon 95°C ase the output powdegree. RS ≤40dB oling, fan speed ran inner temperatuen controller stop war an. aw materials. Con	ort-circuit fault, no ort-circuit wer, decrease 3A per ate regulated by re is too low, fan ran working, fan also stop			
Input Overvoltage Protection Input Polarity Reversal Protection Output Overvoltage Protection Output Polarity Reversal Protection Short-circuit Protection Temperature Protection Temperature protection Noise Thermal methods	Recover after e problen Above 85°C,decrea OTHER PARAMETE Forced air cod temperature, when slowly or stop; when world brand restandards. Mee	liminating the Shoon for long term Shoon for long term Shoon for long term Shoon for long term shoon degree. RS ≤40dB Soling, fan speed randen controller stop worden. aw materials. Const the 2002/95/EC	ort-circuit fault, no ort-circuit wer, decrease 3A per ate regulated by re is too low, fan ran working, fan also stop appliance with EU without cadmium			
Input Overvoltage Protection Input Polarity Reversal Protection Output Overvoltage Protection Output Polarity Reversal Protection Short-circuit Protection Temperature Protection Temperature protection Noise	Recover after e problem Above 85°C,decrea OTHER PARAMETE Forced air cootemperature, when slowly or stop; when standards. Mee hydride, fluoride, proceed and proceed are standards.	liminating the Shoon for long term Shoon for long term Shoon for long term Shoon for long term Shoon degree. RS ≤40dB Soling, fan speed ran inner temperatuen controller stop war an. aw materials. Constitute the 2002/95/EC peculiar smell and	ort-circuit fault, no ort-circuit wer, decrease 3A per ate regulated by re is too low, fan ran working, fan also stop appliance with EU without cadmium toxic substances.All			
Input Overvoltage Protection Input Polarity Reversal Protection Output Overvoltage Protection Output Polarity Reversal Protection Short-circuit Protection Temperature Protection Temperature protection Noise Thermal methods	Recover after e problem Above 85°C,decrea OTHER PARAMETE Forced air cootemperature, when slowly or stop; when standards. Mee hydride, fluoride, proceed and proceed are standards.	liminating the Shoon for long term Shoon for long term Shoon for long term Shoon for long term Shoon degree. RS ≤40dB Soling, fan speed randen controller stop worden. aw materials. Condet the 2002/95/EC deculiar smell and of electrolytic cap	ort-circuit fault, no ort-circuit wer, decrease 3A per ate regulated by re is too low, fan ran working, fan also stop appliance with EU without cadmium			
Input Overvoltage Protection Input Polarity Reversal Protection Output Overvoltage Protection Output Polarity Reversal Protection Short-circuit Protection Temperature Protection Temperature protection Noise Thermal methods	Recover after e problem Above 85°C,decrea OTHER PARAMETE Forced air cootemperature, when slowly or stop; when world brand restandards. Mee hydride, fluoride, prated temperature	liminating the Shoon for long term Shoon for long term Shoon for long term Shoon for long term Shoon degree. RS ≤40dB Soling, fan speed ran inner temperatuen controller stop war an. aw materials. Constitute the 2002/95/EC peculiar smell and	ort-circuit fault, no ort-circuit wer, decrease 3A per ate regulated by re is too low, fan ran working, fan also stop appliance with EU without cadmium toxic substances.All			
Input Overvoltage Protection Input Polarity Reversal Protection Output Overvoltage Protection Output Polarity Reversal Protection Short-circuit Protection Temperature Protection Temperature protection Noise Thermal methods Environment Protection	Recover after e problem Above 85°C,decrea OTHER PARAMETE Forced air cootemperature, when slowly or stop; when standards. Mee hydride, fluoride, proceed and proceed are standards.	liminating the Shoon for long term Shoon for long term Shoon for long term Shoon for long term shoon degree. RS ≤40dB Soling, fan speed rander temperatuen controller stop woran. aw materials. Const the 2002/95/EC peculiar smell and of electrolytic capable.	ort-circuit fault, no ort-circuit wer, decrease 3A per ate regulated by re is too low, fan ran working, fan also stop appliance with EU without cadmium toxic substances.All			
Input Overvoltage Protection Input Polarity Reversal Protection Output Overvoltage Protection Output Polarity Reversal Protection Short-circuit Protection Temperature Protection Temperature protection Noise Thermal methods	Recover after e problem Above 85°C,decrea OTHER PARAMETE Forced air cootemperature, when slowly or stop; when world brand restandards. Mee hydride, fluoride, prated temperature	liminating the Shoon for long term Shoon for long term Shoon for long term Shoon for long term Shoon degree. RS ≤40dB Soling, fan speed randen controller stop worden. aw materials. Condet the 2002/95/EC deculiar smell and of electrolytic cap	ort-circuit fault, no ort-circuit wer, decrease 3A per ate regulated by re is too low, fan ran working, fan also stop appliance with EU without cadmium toxic substances.All			

G.N(kg)	2.4			
Color	Blue/Green (optional)			
Safety	CE, RoHS, PSE,FCC			
EMC	EN61000			
Type of Mechanical Protection	IP21			
ENVIRONMENT				
Humidity	0~90%RH (no condense)			
Altitude	0~3000m			
Operating Temperature	-20°C ~ +40°C			
Storage Temperature	-40°C ~ +75°C			
Atmospheric Pressure	70~106kPa			