## High Conversion Efficiency Wide Range Input Voltage DC12V/24V/48V/96V Syatem Automatic Identification

I-P- SMART1-DC12V/24V/48V/96V-20A MPPT Solar charge Controller. With MPPT, it can target the highest output possibe from PV panels, make efficiency higher upto 30%~60% than traditional PWM ones. It can store energy to different kinds of batteries(Gel,Vented, Sealed, NiCd etc.). For all of our products has passed CE, ROHS, FCC etc.Unlimited connect in parallel.

## **System**



## **Features**

- 1. Peak efficiency upto 99% with MPPT,increasing 30%~60% efficiency than traditional controller.
- 2. 12v/24v/48v/96V system voltage automatic recognize.
- 3. Maximum input PV voltage upto DC300V.
- 4. 105degrees can be sufferred by good components.
- 5. Charge mode: three stages (fast charge, constant charge, floating charge)
- 6. Support kinds of batteries: Gel, Sealed lead acid, vented, NiCd, etc.
- 7. LCD and LEDs show parameters and system information, like PV input voltage, battery voltage, charge current, charge power, etc.
- 8. Port RS232 or connects to PC with upper software to show working state and parameters in 11 languages.
- 9. CE,RoHS certifications approved.
- 10. 2 years warranty;3~10 years extended technical service.

## **Parameter**

| Model:I-P-SMART1-DC12V/24V/48V/96v eries |                              | 20A  |
|--|------------------------------|--|
| Charge Mode                              | Maximum Power Point Tracking |  |
| Method                                   | 3 stages: fast char          | ge(MPPT),constant voltage, floating charge |
| System Type                              | DC12V/24V/48V                | Automatic recognition                      |
| System Voltage                           | 12V system                   | DC9V~DC15V                                 |
|  | 24V system                   | DC18V~DC30V                                |
|  | 48Vsystem                    | DC36V~DC60V                                |
|  | 96Vsystem                    | DC72V~DC120V                               |

| Soft Start Time  | 12V/24V/48V/96v<br>system   | ≤10S   |  |  |
|--|---|--|--|--|
| Dynamic Response<br>Recovery Time  | 12V/24V/48V/96v<br>system   | 500us  |  |  |
| Conversion Efficiency  | 12V/24V/48V/96v<br>system   | ≥96.5%,≤99%  |  |  |
| PV Modules Utilization Rate  | 12V/24V/48V/96v<br>system   | ≥99%   |  |  |
| Input Characteristics  |   |  |  |  |
| MPPT Working Voltage and Range   | 12V system  | DC18V~DC150V   |  |  |
|  | 24V system  | DC34~DC150V  |  |  |
|  | 48V system  | DC65~DC150V  |  |  |
|  | 96V system  | DC125~DC300V   |  |  |
| Low Voltage Input Protection Point   | 12V system  | DC16V  |  |  |
|  | 24V system  | DC30V  |  |  |
|  | 48V system  | DC60V  |  |  |
|  | 96V system  | DC120V   |  |  |
|  | 12V system  | DC22V  |  |  |
| Low Voltage Input Recovery Point   | 24V system  | DC34V  |  |  |
| Low voltage input recovery rollic  | 48V system  | DC65V  |  |  |
|  | 96V system  | DC125V   |  |  |
|  | 12V/24V/48V   | DC123V   |  |  |
| Max DC Voltage   | system  | DC160V   |  |  |
|  | 96V system  | DC300V   |  |  |
| Input Overvoltage Protection Point   | 12V/24V/48V<br>system   | DC150  |  |  |
|  | 96V system  | DC300V   |  |  |
| Input Overvoltage Recovery Point   | 12V/24V/48V<br>system   | DC145V   |  |  |
| linput overvoitage Necovery Foint  | 96V system  | DC295V   |  |  |
|  |   | 280W   |  |  |
|  | 12V system  |  |  |  |
| Max. PV Power  | 24V system  | 560W   |  |  |
|  | 48V system  | 1120W  |  |  |
|  | 96V system  | 2240W  |  |  |
| 0  |   |  |  |  |
| Output Characteristics   |   |  |  |  |
| Output Characteristics<br>Selectable Battery Types (Default typ<br>is GEL battery)   | ne 12V/24V/48V/96Vs<br>ystem  | Sealed lead acid, vented, Gel, NiCd battery<br>(Other types of the batteries also can be defined)  |  |  |
| Selectable Battery Types (Default typ  | ystem<br>12V/24V/48V/96V  | (Other types of the batteries also can be defined)   |  |  |
| Selectable Battery Types (Default typis GEL battery)   | ystem<br>12V/24V/48V/96V<br>system<br>12V/24V/48V/96Vs  | (Other types of the batteries also can be defined)  Please check the charge voltage according to the battery type  |  |  |
| Selectable Battery Types (Default typis GEL battery)  Constant Voltage   | ystem 12V/24V/48V/96V system 12V/24V/48V/96Vs ystem   | (Other types of the batteries also can be defined)  Please check the charge voltage according to the battery type form.  |  |  |
| Selectable Battery Types (Default typis GEL battery)  Constant Voltage  Floating Charge Voltage  | ystem 12V/24V/48V/96V system 12V/24V/48V/96Vs ystem 12V system  | (Other types of the batteries also can be defined)  Please check the charge voltage according to the battery type form.  14.6V   |  |  |
| Selectable Battery Types (Default typis GEL battery)  Constant Voltage   | ystem 12V/24V/48V/96V system 12V/24V/48V/96Vs ystem 12V system 24V system   | (Other types of the batteries also can be defined)  Please check the charge voltage according to the battery type form.  14.6V 29.2V   |  |  |
| Selectable Battery Types (Default typis GEL battery)  Constant Voltage  Floating Charge Voltage  | ystem  12V/24V/48V/96V system  12V/24V/48V/96Vs ystem  12V system  24V system  48V system   | (Other types of the batteries also can be defined)  Please check the charge voltage according to the battery type form.  14.6V 29.2V 58.4V   |  |  |
| Selectable Battery Types (Default typis GEL battery)  Constant Voltage  Floating Charge Voltage  | ystem  12V/24V/48V/96V system  12V/24V/48V/96Vs ystem  12V system  24V system  48V system  96V system   | (Other types of the batteries also can be defined)  Please check the charge voltage according to the battery type form.  14.6V 29.2V   |  |  |
| Selectable Battery Types (Default typis GEL battery)  Constant Voltage  Floating Charge Voltage  | ystem  12V/24V/48V/96V system  12V/24V/48V/96Vs ystem  12V system  24V system 48V system 96V system 12V/24V/48V system  | (Other types of the batteries also can be defined)  Please check the charge voltage according to the battery type form.  14.6V 29.2V 58.4V   |  |  |
| Selectable Battery Types (Default typis GEL battery)  Constant Voltage  Floating Charge Voltage  Over Charge Protection Voltage  | ystem  12V/24V/48V/96V system  12V/24V/48V/96Vs ystem  12V system  24V system 48V system 96V system 12V/24V/48V system 12V/24V/48V system   | (Other types of the batteries also can be defined)  Please check the charge voltage according to the battery type form.  14.6V 29.2V 58.4V 116.8V 20A ±0.02%/°C  |  |  |
| Selectable Battery Types (Default typis GEL battery)  Constant Voltage  Floating Charge Voltage  Over Charge Protection Voltage  Rated Output Current  | ystem  12V/24V/48V/96V system  12V/24V/48V/96Vs ystem  12V system 24V system 48V system 96V system 12V/24V/48V system 12V/24V/48V system 12V/24V/48V system 12V/24V/48V   | (Other types of the batteries also can be defined)  Please check the charge voltage according to the battery type form.  14.6V 29.2V 58.4V 116.8V 20A ±0.02%/°C  |  |  |
| Selectable Battery Types (Default typis GEL battery)  Constant Voltage  Floating Charge Voltage  Over Charge Protection Voltage  Rated Output Current  Temperature Factor  | ystem  12V/24V/48V/96V system  12V/24V/48V/96Vs ystem  12V system 24V system 48V system 96V system 12V/24V/48V system 12V/24V/48V system 12V/24V/48V system 12V/24V/48V system 12V/24V/48V/96V ystem 12V/24V/48V/96V                                    | (Other types of the batteries also can be defined)  Please check the charge voltage according to the battery type form.  14.6V 29.2V 58.4V 116.8V 20A ±0.02%/°C  |  |  |
| Selectable Battery Types (Default typis GEL battery)  Constant Voltage  Floating Charge Voltage  Over Charge Protection Voltage  Rated Output Current  Temperature Factor  Temperature Compensation  | ystem  12V/24V/48V/96V system  12V/24V/48V/96Vs ystem  12V system 24V system 48V system 96V system 12V/24V/48V system 12V/24V/48V system 12V/24V/48V system 12V/24V/48V/96v ystem 12V/24V/48V/96v system 12V/24V/48V/96v                                | (Other types of the batteries also can be defined)  Please check the charge voltage according to the battery type form.  14.6V 29.2V 58.4V 116.8V 20A  ±0.02%/°C  14.2V-(The highest temperature-25°C)*0.3   |  |  |
| Selectable Battery Types (Default types (Selectable Battery) Constant Voltage Floating Charge Voltage  Over Charge Protection Voltage  Rated Output Current  Temperature Factor  Temperature Compensation  Output Ripples(peak)  Output Voltage Stability Precision  | ystem  12V/24V/48V/96V system  12V/24V/48V/96Vs ystem  12V system  24V system 48V system 96V system 12V/24V/48V system 12V/24V/48V system 12V/24V/48V system 12V/24V/48V/96V system 12V/24V/48V/96V system  | (Other types of the batteries also can be defined)  Please check the charge voltage according to the battery type form.  14.6V 29.2V 58.4V 116.8V 20A  ±0.02%/°C  14.2V-(The highest temperature-25°C)*0.3   |  |  |
| Selectable Battery Types (Default typis GEL battery)  Constant Voltage  Floating Charge Voltage  Over Charge Protection Voltage  Rated Output Current  Temperature Factor  Temperature Compensation  Output Ripples(peak)  | ystem  12V/24V/48V/96V system  12V/24V/48V/96Vs ystem  12V system 24V system 48V system 96V system 12V/24V/48V system 12V/24V/48V system 12V/24V/48V system 12V/24V/48V/96v ystem 12V/24V/48V/96v system 12V/24V/48V/96v                                | (Other types of the batteries also can be defined)  Please check the charge voltage according to the battery type form.  14.6V 29.2V 58.4V 116.8V 20A  ±0.02%/°C  14.2V-(The highest temperature-25°C)*0.3  200mV  ≤±1.5%  |  |  |
| Selectable Battery Types (Default types (Selectable Battery) Constant Voltage Floating Charge Voltage  Over Charge Protection Voltage  Rated Output Current  Temperature Factor  Temperature Compensation  Output Ripples(peak)  Output Voltage Stability Precision  | ystem  12V/24V/48V/96V system  12V/24V/48V/96Vs ystem  12V system 24V system 48V system 96V system 12V/24V/48V system 12V/24V/48V system 12V/24V/48V system 12V/24V/48V/96v ystem 12V/24V/48V/96v system 12V/24V/48V/96v                                | (Other types of the batteries also can be defined)  Please check the charge voltage according to the battery type form.  14.6V 29.2V 58.4V 116.8V 20A  ±0.02%/°C  14.2V-(The highest temperature-25°C)*0.3   |  |  |
| Selectable Battery Types (Default typis GEL battery)  Constant Voltage  Floating Charge Voltage  Over Charge Protection Voltage  Rated Output Current  Temperature Factor  Temperature Compensation  Output Ripples(peak)  Output Voltage Stability Precision  Display   | ystem  12V/24V/48V/96V system  12V/24V/48V/96Vs ystem  12V system 24V system 48V system 96V system 12V/24V/48V system 12V/24V/48V system 12V/24V/48V system 12V/24V/48V/96v ystem 12V/24V/48V/96v system 12V/24V/48V/96v                                | (Other types of the batteries also can be defined)  Please check the charge voltage according to the battery type form.  14.6V 29.2V 58.4V 116.8V 20A  ±0.02%/°C  14.2V-(The highest temperature-25°C)*0.3  200mV  ≤±1.5%  Input, output parameter and output power etc  |  |  |
| Selectable Battery Types (Default types GEL battery)  Constant Voltage  Floating Charge Voltage  Over Charge Protection Voltage  Rated Output Current  Temperature Factor  Temperature Compensation  Output Ripples(peak)  Output Voltage Stability Precision  Display  LCD display  LED display  Software Control through PC(communication)   | ystem  12V/24V/48V/96V system  12V/24V/48V/96Vs ystem  12V system 24V system 48V system 96V system 12V/24V/48V system 12V/24V/48V system 12V/24V/48V system 12V/24V/48V/96V system 12V/24V/48V/96V system 12V/24V/48V/96V system 12V/24V/48V/96V system | (Other types of the batteries also can be defined)  Please check the charge voltage according to the battery type form.  14.6V 29.2V 58.4V 116.8V 20A  ±0.02%/°C  14.2V-(The highest temperature-25°C)*0.3  200mV ≤±1.5%  Input, output parameter and output power etc (check the LCD display instruction)  3 LEDs indicates: Fault indicate light, charge indicate light,   |  |  |
| Selectable Battery Types (Default types GEL battery)  Constant Voltage  Floating Charge Voltage  Over Charge Protection Voltage  Rated Output Current  Temperature Factor  Temperature Compensation  Output Ripples(peak)  Output Voltage Stability Precision  Display  LCD display  LED display  Software Control through PC(communication)   | ystem  12V/24V/48V/96V system  12V/24V/48V/96Vs ystem  12V system 24V system 48V system 96V system 12V/24V/48V system 12V/24V/48V system 12V/24V/48V system 12V/24V/48V/96V system 12V/24V/48V/96V system 12V/24V/48V/96V system 12V/24V/48V/96V system | (Other types of the batteries also can be defined)  Please check the charge voltage according to the battery type form.  14.6V 29.2V 58.4V 116.8V 20A  ±0.02%/°C  14.2V-(The highest temperature-25°C)*0.3  200mV  ≤±1.5%  Input, output parameter and output power etc (check the LCD display instruction)  3 LEDs indicates: Fault indicate light, charge indicate light, power source indicate light(check the LED instruction)  RS232 (matching) or LAN(optional)  |  |  |
| Selectable Battery Types (Default types (Gelectable Battery)  Constant Voltage  Floating Charge Voltage  Over Charge Protection Voltage  Rated Output Current  Temperature Factor  Temperature Compensation  Output Ripples(peak)  Output Voltage Stability Precision  Display  LCD display  LED display  Software Control through PC(communication)  Input Low Voltage Protection   | ystem  12V/24V/48V/96V system  12V/24V/48V/96Vs ystem  12V system 24V system 48V system 96V system 12V/24V/48V system 12V/24V/48V system 12V/24V/48V system 12V/24V/48V/96V system 12V/24V/48V/96V system 12V/24V/48V/96V system 12V/24V/48V/96V system | (Other types of the batteries also can be defined)  Please check the charge voltage according to the battery type form.  14.6V 29.2V 58.4V 116.8V 20A  ±0.02%/°C  14.2V-(The highest temperature-25°C)*0.3  200mV  ≤±1.5%  Input, output parameter and output power etc (check the LCD display instruction)  3 LEDs indicates: Fault indicate light, charge indicate light, power source indicate light(check the LED instruction)  RS232 (matching) or LAN(optional)  Check the input characteristics   |  |  |
| Selectable Battery Types (Default types (Gelectable Battery)  Constant Voltage  Floating Charge Voltage  Over Charge Protection Voltage  Rated Output Current  Temperature Factor  Temperature Compensation  Output Ripples(peak)  Output Voltage Stability Precision  Display  LCD display  LED display  Software Control through PC(communication)  Input Low Voltage Protection  Input Overvoltage Protection  Input Overvoltage Protection       | ystem  12V/24V/48V/96V system  12V/24V/48V/96Vs ystem  12V system 24V system 48V system 96V system 12V/24V/48V system 12V/24V/48V system 12V/24V/48V system 12V/24V/48V/96V system 12V/24V/48V/96V system 12V/24V/48V/96V system 12V/24V/48V/96V system | (Other types of the batteries also can be defined)  Please check the charge voltage according to the battery type form.  14.6V 29.2V 58.4V 116.8V 20A  ±0.02%/°C  14.2V-(The highest temperature-25°C)*0.3  200mV ≤±1.5%  Input, output parameter and output power etc (check the LCD display instruction)  3 LEDs indicates: Fault indicate light, charge indicate light, power source indicate light(check the LED instruction)  RS232 (matching) or LAN(optional)  Check the input characteristics Check the input characteristics                                      |  |  |
| Selectable Battery Types (Default types (Gelectable Battery)  Constant Voltage  Floating Charge Voltage  Over Charge Protection Voltage  Rated Output Current  Temperature Factor  Temperature Compensation  Output Ripples(peak)  Output Voltage Stability Precision  Display  LCD display  LED display  Software Control through PC(communication)  Input Low Voltage Protection  Input Overvoltage Protection  Input Polarity Reversal Protection | ystem  12V/24V/48V/96V system  12V/24V/48V/96Vs ystem  12V system 24V system 48V system 96V system 12V/24V/48V system 12V/24V/48V system 12V/24V/48V system 12V/24V/48V/96V system 12V/24V/48V/96V system 12V/24V/48V/96V system 12V/24V/48V/96V system | (Other types of the batteries also can be defined)  Please check the charge voltage according to the battery type form.  14.6V  29.2V  58.4V  116.8V  20A  ±0.02%/°C  14.2V-(The highest temperature-25°C)*0.3  200mV  ≤±1.5%  Input, output parameter and output power etc (check the LCD display instruction)  3 LEDs indicates: Fault indicate light, charge indicate light, power source indicate light(check the LED instruction)  RS232 (matching) or LAN(optional)  Check the input characteristics Check the input characteristics Check the input characteristics |  |  |
| Selectable Battery Types (Default types (Gelectable Battery)  Constant Voltage  Floating Charge Voltage  Over Charge Protection Voltage  Rated Output Current  Temperature Factor  Temperature Compensation  Output Ripples(peak)  Output Voltage Stability Precision  Display  LCD display  LED display  Software Control through PC(communication)  Input Low Voltage Protection  Input Overvoltage Protection  Input Overvoltage Protection       | ystem  12V/24V/48V/96V system  12V/24V/48V/96Vs ystem  12V system 24V system 48V system 96V system 12V/24V/48V system 12V/24V/48V system 12V/24V/48V system 12V/24V/48V/96V system 12V/24V/48V/96V system 12V/24V/48V/96V system 12V/24V/48V/96V system | (Other types of the batteries also can be defined)  Please check the charge voltage according to the battery type form.  14.6V 29.2V 58.4V 116.8V 20A  ±0.02%/°C  14.2V-(The highest temperature-25°C)*0.3  200mV ≤±1.5%  Input, output parameter and output power etc (check the LCD display instruction)  3 LEDs indicates: Fault indicate light, charge indicate light, power source indicate light(check the LED instruction)  RS232 (matching) or LAN(optional)  Check the input characteristics Check the input characteristics                                      |  |  |

| Short-circuit Protection      | Recover after eliminating the Short-circuit fault, no problem for long term Short-circuit  |  |
|-------------------------------|--|--|
| Temperature Protection        | 95℃  |  |
| Temperature protection        | Above 85°C,decrease the output power, decrease 3A per degree.  |  |
| Other Parameters              |  |  |
| Noise                         | ≤40dB  |  |
| Thermal methods               | Forced air cooling, fan speed rate regulated by temperature, when inner temperature is too low, fan ran slowly or stop; when controller stop working, fan also stop ran. |  |
| Components                    | World brand raw materials. Compliance with EU standards. All rated temperature of electrolytic capacitors not less than 105°C  |  |
| Smell                         | No peculiar smell and toxic substances.  |  |
| Environment Protection        | Meet the 2002/95/EC,no cadmium hydride and fluoride  |  |
| Physical                      |  |  |
| Measurement DxWxH (mm)        | 270*185*90   |  |
| N.G(kg)                       | 3  |  |
| G.N(kg)                       | 4.5  |  |
| Color                         | Blue/Green (optional)  |  |
| Safety                        | CE, RoHS, PSE,FCC  |  |
| EMC                           | EN61000  |  |
| Type of Mechanical Protection | IP21   |  |
| Environment                   |  |  |
| Humidity                      | 0~90%RH ( no condense)   |  |
| Altitude                      | 0~3000m  |  |
| Operating Temperature         | -20°C ~ +40°C  |  |
| Storage Temperature           | -40°C ~ +75°C  |  |
| Atmospheric Pressure          | 70~106kPa  |  |

RS232 Connect way

