

solar system controller 12V/24V/36V/48V 80A [MPPT solar charge controller](#)



Feature

1. It has an efficient MPPT algorithm, MPPT efficiency $\geq 99.5\%$ and converter efficiency up to 98%.
2. Charge mode: three stages (constant current, constant voltage, floating charge), it prolongs service life of the batteries.
3. Four types of load mode selection: ON/OFF, PV voltage control, Dual Time control, PV+Time control.
4. Battery system voltage automatic recognition.
5. Three kinds of commonly used lead-acid battery (Seal\Gel\Flooded) parameter settings can be selected by the user, and the user can also customize the parameters for other battery charging.
6. It has a current limiting charging function. When the power of PV is too large, the controller automatically keeps the charging power, and the charging current will not exceed the rated value.
7. Support multi-machine parallel to realize system power upgrade.
8. High definition LCD display function to check the device running data and working status, also can support modify the controller display parameter.
9. RS485 communication, we can offer communication protocol to convenient user's integrated management and secondary development.
10. Support PC software monitoring and WiFi module to realize APP cloud monitoring.
11. CE, RoHS, FCC certifications approved, we can assist clients to pass various certifications.
12. 2 years warranty, and 2~10 years extended warranty service also can be provided.



Parameter

MASTER series			48BL-80A	48BH-80A
Product category	Controller Properties		MPPT (maximum power point tracking)	
	MPPT efficiency		≥99.5%	
	Standby power		0.5W~1.2W	
	System voltage		Automatic recognition	48V
	Heat-dissipating method		Air cooling	
Input Characteristics	Max.PV input voltage(VOC)		DC150V	DC300V
	Start the charge voltage point		Battery voltage + 3V	Battery voltage + 10V
	Low input voltage protection point		Battery voltage + 2V	Battery voltage + 5V
	Over voltage protection point		DC150V	DC300V
	Rated PV power	12V system	1040W	□
		24V system	2080W	□
		36V system	3120W	□
		48V system	4160W	4160W
		96V system	□	□
Charge Characteristics	Selectable Battery Types(Default Gel battery)		Sealed lead acid, Gel battery, Flooded (Other types of the batteries also can be defined)	
	Charge rated current		80A	80A
	Charging Method		3-Stage: constant current(fast charging)-constant voltage-floating charge	
LOAD Characteristics	Load voltage		The same as the battery voltage	
	Load rated current		80A	80A
	Load control mode		On\Off mode, PV voltage control mode, Dual-time control mode, PV + Time control mode	
Display & Communication	Display mode		High-definition LCD segment code backlight display	
	Communication mode		8-pin RJ45 port/RS485/support PC software monitoring/support WiFi module to realize APP cloud monitoring	

Other Parameters	Protect function	Input-output over \ under voltage protection,Prevention of connection reverse protection,battery shedding protection etc.
	Operation Temperature	-20℃~+50℃
	Storage Temperature	-40℃~+75℃
	IP(Ingress protection)	IP43
	Max. connection size	50mm2
	Net Weight (kg)	7.1
	Gross Weight (kg)	8.8
	Product Size□mm□	420*280*95
	Packing Size(mm)	510*368*210

Upper Computer Software and Test Software

MPPT Solar MonitorV1.0

IPANDEE
MPPT Model: Explorer-M2460
Firmware: V2.6
Serial: 9246111120220419
Message: Click [START EDIT] to modify parameters!

Com Port: COM1
BaudRate: 9600
Address: 1
Opened
CLOSE
CHECK ADDRESS
STOP MONITOR
START EDIT
SET TIME
RESTORE
DATA CORRECTION

Running State
Standby

Real-time Data
PV Volt: 0.1V
BAT Volt: 14.2V
LoadVolt: 14.1V
CHG Curr: 0.0A
LoadCurr: 0.4A
CHG Power: 0W
LoadPower: 5W
InnerTemp: 27.0℃
BAT Temp: 25.0℃
Alarm Tip: PV Low

Electricity Statistics
Day CHG: 0.0kWh
Month CHG: 0.0kWh
Total CHG: 0.0kWh
Day Used: 0.5kWh
MonthUsed: 0.5kWh
TotalUsed: 0.5kWh

Bat Parameters Of Controller
Bat Category: FLD
System Volt: (Auto)12 V
C.V. Charge: 14.6 V
Float Charge: 13.8 V
Equalizing V: 14.8 V
Equalizing T: 30 min
Max Chg Curr: 60.0 A
Max LoadCurr: 30.0 A
Battery Over: 15.0 V
Over Recover: 14.8 V
Battery Low: 10.5 V
Low Recover: 11.0 V

Bat Parameters Set
Select Battery
BatType: FLD
Sys. Volt: Auto
Max CHG -I: 60.0 A
Max Load-I: 30.0 A
SAVE

Lead Acid Battery(9~15V)
C.V. Charge: 14.6 V
Equalizing V: 14.8 V
Float Charge: 13.8 V
Equalizing T: 30 min
Battery Over: 15.0 V
Over Recover: 14.8 V
Battery Low: 10.5 V
Low Recover: 11.0 V
SAVE


Lithium Battery
Charge Volt: 14.6 V
Nominal Volt: 12.8 V
Battery Over: 15.0 V
Over Recover: 14.8 V
Battery Low: 7.5 V
Low Recover: 6.0 V
SAVE

Load Output Parameters Of Controller
Load Control Mode: On Mode
Note:If Vbat exceeds the protection,will turn off!

Load Output Set
Light Mode
On Load->PV Low: 10.0 V
Off Delay: 10 min
OffLoad->PV OK: 10.0 V
Off Delay: 10 min
Dual Timer Mode
Timer1->On Time: 0 : 0
Off Time: 0 : 0
Timer2->On Time: 0 : 0
Off Time: 0 : 0
Light-Time Mode
Dark->On Load->PvLow: 10.0 V
On Hour: 0 H
Dawn->OffLoad->Pv Ok: 10.0 V
On Hour: 0 H
Load Mode Selection:
On Mode
SAVE

Copyright(C)IPANDEE [2022/1]
2022- 4-19 15:37:33
Bytes received: 378468
Bytes sent: 99320
Language: English
切换为中文

System connection diagram



Parallel connection diagram

